



G59/3 TYPE TEST VERIFICATION REPORT

Type Tested reference number		GW4000-DT/GW5000-DT/GW6000-DT/GW4000L-DT/ GW5000L-DT/GW6000L-DT/GW8000-DT/GW9000-DT/ GW10KN-DT	
System supplier name		Jiangsu GoodWe Power Supply Technology Co.,Ltd.	
Address		NO.189 Kun Lun Shan Road, Suzhou New District, Jiangsu,china	
Tel	+86 512 6239 7998	Fax	+86 512 6239 7972
E:mail	service@goodwe.com.cn	Web site	http://www.goodwe.com.cn
Maximum export capacity, use separate sheet if more than one connection option.	4	kW Three phase	
	5	kW Three phase	
	6	kW Three phase	
	8	kW Three phase	
	9	kW Three phase	
	10	kW Three phase	
<p>System supplier declaration.</p> <p>- I certify on behalf of the company named above as a supplier of a Generating Unit, that all products supplied by the company with the above Type Test reference number will be manufactured and tested to ensure that they perform as stated in this document, prior to shipment to site and that no site modifications are required to ensure that the product meets all the requirements of G59/3.</p>			
Signed		On behalf of	

Power Quality. Harmonics. Generating Unit tested to BS EN 61000-3-12								
Generating Unit rating per phase (rpp)			10.0		kVA		Harmonic % = Measured Value (Amps) x 23 / rating per phase (kVA)	
100% of rated output							Limit in BS EN 61000-3-12	
L1		L2		L3				
Measured Value (A)	%	Measured Value (A)	%	Measured Value (A)	%	1 phase	3 phase	
2	0.0920	0.10%	0.0625	0.43%	0.0495	0.34%	8%	8%
3	0.0847	0.09%	0.0733	0.51%	0.0385	0.27%	21.6%	---
4	0.1535	0.16%	0.1388	0.96%	0.1521	1.06%	4%	4%
5	0.0377	0.04%	0.0225	0.16%	0.0492	0.34%	10.7%	10.7%
6	0.0350	0.04%	0.0216	0.15%	0.0218	0.15%	2.67%	2.67%
7	0.0522	0.05%	0.0611	0.42%	0.0511	0.36%	7.2%	7.2%
8	0.0775	0.08%	0.0688	0.48%	0.0627	0.44%	2%	2%
9	0.0150	0.02%	0.0087	0.06%	0.0101	0.07%	3.8%	---
10	0.0357	0.04%	0.0396	0.27%	0.0339	0.24%	1.6%	1.6%
11	0.0327	0.03%	0.0393	0.27%	0.0327	0.23%	3.1%	3.1%
12	0.0152	0.02%	0.0113	0.08%	0.0062	0.04%	1.33%	1.33%
13	0.0467	0.05%	0.0378	0.26%	0.0493	0.34%	2%	2%
THD	1.7078	11.90%	1.5380	10.72%	1.5092	10.52%	23%	13%
PWHD	1.7852	12.44%	1.6530	11.52%	1.5752	10.98%	23%	22%
At 45-55% of rated output							Limit in BS EN 61000-3-12	
L1		L2		L3				

	Measured Value (A)	%	Measured Value (A)	%	Measured Value (A)	%	1 phase	3 phase
2	0.1077	0.75%	0.0827	0.58%	0.1086	0.76%	8%	8%
3	0.0897	0.63%	0.0835	0.58%	0.0379	0.26%	21.6%	---
4	0.1526	1.06%	0.1352	0.94%	0.1513	1.05%	4%	4%
5	0.0830	0.58%	0.0376	0.26%	0.0820	0.57%	10.7%	10.7%
6	0.0463	0.32%	0.0322	0.22%	0.0228	0.16%	2.67%	2.67%
7	0.0973	0.68%	0.1143	0.80%	0.1018	0.71%	7.2%	7.2%
8	0.1176	0.82%	0.1056	0.74%	0.0939	0.65%	2%	2%
9	0.0242	0.17%	0.0191	0.13%	0.0128	0.09%	3.8%	---
10	0.0617	0.43%	0.0693	0.48%	0.0607	0.42%	1.6%	1.6%
11	0.0749	0.52%	0.0848	0.59%	0.0721	0.50%	3.1%	3.1%
12	0.0154	0.11%	0.0136	0.10%	0.0062	0.04%	1.33%	1.33%
13	0.0880	0.61%	0.0767	0.53%	0.0971	0.68%	2%	2%
THD	1.6025	11.16%	1.5580	10.86%	1.5251	10.63%	23%	13%
PWHD	1.7130	11.94%	1.6862	11.75%	1.6229	11.31%	23%	22%

Power Quality. Voltage fluctuations and Flicker. The tests should be carried out on a single Generating Unit. Results should be normalised to a standard source impedance or if this results in figures above the limits set in BS EN 61000-3-11 to a suitable Maximum Impedance.

	Starting			Stopping			Running	
	d max	d c	d(t)	d max	d c	d(t)	P st	P It 2 hours
Measured Values at test impedance	-	-	-	-	-	-	-	-
Normalised to standard impedance	0.12%	0.08%	0.00%	0%	0%	0%	0.07	0.07
Normalised to required maximum impedance	-	-	-	-	-	-	-	-
Limits set under BS EN 61000-3-11	4%	3.3%	3.3%	4%	3.3%	3.3%	1.0	0.65
Test Impedance	R	-	Ω	XI	-	Ω		
Standard Impedance	R	0.4	Ω	XI	0.25	Ω		
Maximum Impedance	R	-	Ω	XI	-	Ω		

Power quality. DC injection.

Test power level	10%	55%	100%
Recorded value in Amps	L1: 7.43mA L2: 5.88mA L3: 13.98mA	L1: 11.10mA L2: 1.76mA L3: 13.42mA	L1: 0.20mA L2: 6.08mA L3: 5.59mA
as % of rated AC current	L1: 0.05% L2: 0.04% L3: 0.09%	L1: 0.07% L2: 0.01% L3: 0.09%	L1: 0.001% L2: 0.040% L3: 0.037%
Limit	0.25%	0.25%	0.25%

Power Quality. Power factor. The tests should be carried out on a single Generating Unit. Test are to be carried out at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.

	216.2V	230V	253V	Measured at three voltage levels and at full output. Voltage to be maintained within + or – 1.5% of the stated level during the test.
Measured value	0.999	0.999	0.999	
Limit	>0.95	>0.95	>0.95	

Protection. Frequency tests

Function	Setting		Trip test		“No-trip tests”	
	Frequency	Time delay	Frequency	Time delay	Frequency /time	Confirm no trip
O/F stage 1	47.5Hz	20s	47.48 Hz	20.18s	51.3Hz 95s	no trip
O/F stage 2	47Hz	0.5s	46.98 Hz	794.8ms	51.8Hz 89.98s	no trip
					52.2Hz 0.48s	no trip
U/F stage 1	51.5Hz	90s	51.52 Hz	90.18s	47.7Hz 25s	no trip
U/F stage 2	52Hz	0.5s	52.02Hz	871.5ms	47.2Hz 19.98s	no trip
					46.8 Hz 0.48s	no trip

Protection. Voltage tests

Function	Setting		Trip test		"No trip-tests" All phases at same voltage	
	Voltage	Time delay	Voltage	Time delay	Voltage /time	Confirm no trip
O/V stage 1	262.2V	1.0s	263.2 V	1.48s	262.2V 1.48 s	no trip
O/V stage 2	273.7V	0.5s	274.7 V	944.2ms	273.7V 0.98s	no trip
U/V stage 1	200.1V	2.5s	199.1 V	2.89s	201.1V 3.5s	no trip
U/V stage 2	184V	0.5s	183 V	906.4ms	185.0V 2.48s	no trip

Protection. Loss of Mains test and single phase test.

Test Power and imbalance	33%	66%	100%	33%	66%	100%
	-5% Q	-5% Q	-5% P	+5% Q	+5% Q	+5% P
Trip time. Limit is 0.5s	0.386	0.421	0.417	0.408	0.375	0.412

Protection. Frequency change, Stability test

	Start Frequency	Change	End Frequency	Confirm no trip
Positive Vector Shift	49.5Hz	+9 degrees		no trip
Negative Vector Shift	50.5Hz	- 9 degrees		no trip
Positive Frequency drift	49.5Hz	+0.19Hzs ⁻¹	51.5Hz	no trip
Negative Frequency drift	50.5Hz	-0.19Hzs ⁻¹	47.5Hz	no trip

Protection. Re-connection timer. The tests should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1

Test should prove that the reconnection sequence starts in no less than 20s for restoration of voltage and frequency to within the stage 1 settings of table 10.5.7.1

Time delay setting (s)	Measured delay (s)	Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of table 10.5.7.1.			
20s	51.2s	At 266.2V	At 196.1V	At 47.4Hz	At 51.6Hz
Confirmation that the Generating Unit does not re-connect		no reconnection	no reconnection	no reconnection	no reconnection

Fault level contribution.

For machines with electro-magnetic output			For Inverter output		
Parameter	Symbol	Value	Time after fault	Volts	Amps
Peak Short Circuit current	i_p	---	20ms	9.8V	321mA
Initial Value of aperiodic current	A	---	100ms	9.5V	261mA
Initial symmetrical short-circuit current*	I_k	---	250ms	9.3V	181mA
Decaying (aperiodic) component of short circuit current*	i_{DC}	---	500ms	9.1V	125mA
Reactance/Resistance Ratio of source*	X/R	---	Time to trip	710 μ s	

Self-Monitoring solid state switching	NA
It has been verified that in the event of the solid state switching device failing to disconnect the Generating Unit, the voltage on the output side of the switching device is reduced to a value below 50 Volts within 0.5 seconds	

Additional comments
GW4000-DT/GW5000-DT/GW6000-DT/GW4000L-DT/GW5000L-DT/ GW6000L-DT/GW8000-DT/GW9000-DT is similar to GW10KN-DT in circuit and construction except for output rating of current and power. The test result can refer to GW10KN-DT.